8-Channel Analog Input Module CE Model ADAM-4017

The ADAM-4017 is a 16-bit, 8-channel analog input module that provides programmable input ranges on all channels. This module is an extremely cost-effective solution for industrial measurement and monitoring applications. 3000VDC optical isolation between the analog input and the module protects the module and peripherals from damage due to high input-line voltages.

It offers signal conditioning, A/D conversion, and RS-485 communication functions. The module protects peripheral equipment from ground loops and power surges by providing optical isolation of the A/D input and transformer based isolation up to 3000 VDC.

The ADAM-4017 uses a 16-bit microprocessor-controlled sigma-delta A/D converter to convert sensor voltage or current into digital data. The digital data is then translated into engineering units. When prompted by the host computer, the module sends the data to the host through a standard RS-485 interface.



Specifications:

Effective Resolution: Channels: Input Type: Input Range: Isolation Voltage: Fault and Over Voltage Protection: Sampling Rate: Input Impedance: Bandwidth: Accuracy: Zero Drift: Span Drift: CMR @ 50/60 Hz: **Communication Output:** Baud Rate: Data Format: **Operating Temperature:** Storage Temperature: Humidity: Power: Compliances:

16-bit 6 differential, 2 single-ended mV. V. mA ±150 mV, ±500 mV, ±1 V, ±5 V, ±10 V, ±20 mA 3000 VDC Withstands over voltage up to ±35 V 10 samples per second (total) 20M ohms 13.1 Hz @ 50 Hz, 15.7 Hz @ 60 Hz ±0.1% or better $\pm 6 \,\mu V$ per degree Celsius ±25 ppm per degree Celsius 92 dB min. RS-485 (2-wire) 1200, 2400, 4800, 9600, 19.2K, 38.4K, 57.6K, 115.2K 8 data bits, no parity, 1 stop bit (asynchronous) 14 to 158°F (-10 to 70°C) -13 to 185°F (-25 to 85°C) 0 to 95% (non-condensing) Unregulated 10-30 VDC (1.2 watts) FCC Class A and CE marked

B&B Electronics -- September 2001

